



Tech Info Library

A/UX: Setup for Modem Autoanswer (8/94)

Article Created: 29 October 1990

Article Reviewed/Updated: 25 August 1994

TOPIC -----

What setting is necessary to have a 1200 baud modem autoanswer from the modem port?

DISCUSSION -----

In A/UX, if you have a problem talking with the modem, first try running `stty -g /dev/tty0 -modem`. This will disable modem control on the modem port. In the `/etc/inittab` subdirectory, make two changes to the line for the modem port as follows:

change the "off" to "respawn"

change the "at_9600" to "mo_1200"

Note: If you have a 2400 baud modem, the last expression should be "mo_2400".

Article Change History:

25 Aug 1994 - Reviewed and updated.

Support Information Services

Copyright 1990, 1994 Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 6476