



Tech Info Library

Color Classic & LC 520: Premature Start-up Problems (7/93)

Article Created: 26 July 1993

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

A Macintosh Color Classic begins booting immediately upon hitting the power switch in the back, without having to press the power key on the keyboard, which should be necessary.

Also, when trying to Shut Down, the machine reboots itself automatically.

This has happened with a Macintosh LC 520 as well.

DISCUSSION -----

Some Color Classic Analog Board/Power Supply service modules (p/n 661-0732) and some LC 520 analog board service modules (P/N 661-0813) may be incorrectly configured. If one of these boards is installed in a Color Classic or LC 520, the unit will demonstrate the problem symptoms described above.

These incorrectly configured Analog Board/Power Supply modules may be identified by a black or metal jumper installed at location BD11 (near the focus control knobs). This location is pertinent only to "Rev. C" boards. Earlier revisions won't have a jumper at this location. When the jumper is removed, the unit will operate properly. If you encounter one of these boards, the problem is easily corrected by removing the jumper.

Copyright 1993, Apple Computer, Inc.

Keywords: hts

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 12832