



Tech Info Library

Network Server 500 & 700: Peripherals Troubleshooting (2/96)

Article Created: 23 February 1996

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

This article provides peripherals troubleshooting steps for your Network Server 500 or Network Server 700.

DISCUSSION -----

Symptom: Cursor does not move

Step 1

Check mouse connection.

Step 2

Inspect inside of mouse for buildup of dirt or other contaminants. Clean mouse if necessary.

Step 3

If mouse was connected to keyboard, connect mouse to computer ADB port instead. If mouse works, replace keyboard.

Step 4

Replace ADB cable.

Step 5

If mouse does not work in any ADB port on computer, replace mouse.

Step 6

Replace logic board. Retain customer's DIMMs.

Step 7

Replace processor card.

Symptom: Cursor moves, but clicking mouse button has no effect

Step 1

If mouse was connected to keyboard, connect mouse to computer ADB port instead.

If mouse works, replace keyboard.

Step 2

If mouse does not work in any ADB port on computer, replace mouse.

Step 3

Replace logic board. Retain customer's DIMMs.

Symptom: No response to any key on keyboard

Step 1

Verify that server is properly configured to connect to a serial terminal.
(Refer to "Setting Up the Network Server" for information on how to connect the server to a serial terminal.)

Step 2

Verify that keyboard is an ADB-compatible extended keyboard.

Step 3

Check keyboard connection to ADB port.

Step 4

Replace keyboard cable.

Step 5

Replace keyboard.

Step 6

Replace logic board. Retain customer's DIMMs.
Copyright 1996, Apple Computer, Inc.

Keywords: ksts,hts

=====
This information is from the Apple Technical Information Library.

19960226 16:03:23.00

Tech Info Library Article Number: 19401