



Tech Info Library

Apple IIc: Serial port interfacing (2 of 2)

Port 2 uses the same commands, with the differences and additions listed below. Each command for Port 2 must be preceded by a CTRL-A.

nnn	same
nnB	same
nD	same
I	same
K	same
L	same
nP	same
Q	Quit Terminal Mode
R	same
S	same
T	Enter Terminal Mode. Use this command after IN#2 only. If you follow this command by PR#2, the IIc will echo input to output. (NOTE: If the other device is also echoing input to output, entering the first character will cause an infinite loop. Use CTRL-RESET to get out.
Z	same
CTRL-T	When issued from a remote device, this command puts the IIc in terminal mode if IN#2 is already in effect. The command is the same as CTRL-T typed locally.
CTRL-R	When issued from a remote device, this command undoes the terminal mode command. If IN#2 and PR#2 are in effect, the remote keyboard and display become the input and output devices of the local IIc. The command is the same as CTRL-A Q typed

locally.
Apple Technical Communications

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 311