



# Tech Info Library

## Apple Modem 300/1200: Configuring it with the Apple IIe

### I. Switch settings

#### A. For 300 baud:

##### 1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7
	ON	X			X	X	X	X		ON	X		X	X		X	
SW1										SW2							
	OFF		X	X						OFF		X			X		X
		1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

##### 2. Modem:

UP				X	
DOWN	X				
	1	2	3		
	CD	BC	DTR		

-- Switch 2 can be up or down; it isn't used.

#### B. For 1200 baud:

##### 1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7
	ON		X	X	X	X	X	X		ON	X		X	X		X	
SW1										SW2							
	OFF	X								OFF		X			X		X
		1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

##### 2. Modem:

UP			X	X	
DOWN	X				
	1	2	3		
	CD	BC	DTR		

II. Connection:

A. Cable IIe: Apple Service Part Number 590-0121

Super Serial Interface Card	Apple Modem 300/1200
DB-25	DB-9
1	8
2	9
3	5
6	2
7	3
8,5	7
20	6

Apple Technical Communications

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1773