



Tech Info Library

DOS Tool Kit: HRCG -- Switching it on and off

The High-Res Character Generator can be turned on and off under software control. The following two subroutines will switch back and forth. The software was written assuming the variable "ADRS" is assigned as it is in the subroutine starting at line 2000 of MAXWELL on the Tool Kit diskette.

```
3000  REM          TURN OFF HRCG
3010  PRINT CHR$(4);"PR#0"
3020  PRINT CHR$(4);"IN#0"
3030  HOME
3040  TEXT
3050  RETURN
4000  REM          TURN ON HRCG
4010  CALL ADRS + 3
4020  RETURN
```

Beware: the HRCG overwrites the text screen when outputting to the High-Res screen. It will destroy any information there. You will have to rewrite the text screen after using HRCG.

Apple Tech Notes

Keywords: <None>

=====
This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 548