



Tech Info Library

AppleLine: Pinouts (10/94)

Article Created: 12 May 1986

Article Reviewed/Updated: 18 October 1994

TOPIC -----

What are the pinouts and functions for the AppleLine?

DISCUSSION -----

DB-25

Connector Mnemonic Signal Name, Data/Signal Direction

1	SNG	Shield ground
2	TXD, Tx	Transmit Data, Out
3	RCD, Rx	Receive Data, In
4	RTS	Request to Send, Out
5	CTS	Clear to Send, In
6	DSR	Data Set Ready, In
7	GND	Ground
8	DCD	Data Carrier Detect, In
9		No connection
10		No connection
11		No connection
12	CH	Data signal rate selector, In
13		No connection
14		No connection
15		No connection
16		No connection
17		No connection
18		No connection
19		No connection
20	DTR	Terminal Ready Signal, Out
21		No connection
22	CE	Ring indicator, In
23		No connection
24		No connection
25		No connection

Article Change History:

18 Oct 1994 - Reviewed for technical accuracy, revised formatting.

Support Information Services
Copyright 1986-94, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1184