



# Tech Info Library

## Performa 460, 466, 467: RAM and VRAM Specifications (10/93)

Article Created: 1 October 1993

TOPIC -----

This article describes the RAM and VRAM specifications for the Performa 460, 466 and 467.

DISCUSSION -----

RAM

---

The Performa 460, 466 and 467 has 4 megabytes (MB) of memory soldered to the logic board and a single 72-pin SIMM RAM expansion socket.

The Performa 460, 466 and 467 can accomodate 1MB, 2MB, 4MB, 8MB, 16MB and 32MB RAM SIMMs. They do not support 256K SIMMs. You must use 72-pin fast-paged mode SIMMs with 80ns access time or faster.

Possible RAM configurations are 4MB, 5MB, 6MB, 8MB, 12MB, 20MB, and 36MB.

VRAM

----

The Performa 460, 466 and 467 have 512K of VRAM soldered to their logic board and have a single VRAM expansion socket. They can be expanded to 768K by adding a single 100ns 256K VRAM SIMM.

Copyright 1993, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 13583