



Tech Info Library

DAL: Common F Messages Coming From VTAM DAL Server to a

Article Created: 13 November 1992

TOPIC -----

This article describes the most frequent F Messages coming from a VTAM DAL server to a client.

DISCUSSION -----

VTAM errors are documented in the VTAM Installation Guide and these errors never get sent to the client. There are 'F Messages' which can come from the VTAM server to the client, and the most common are:

F000000001	Terminal I/O Error
F000000004	Invalid or Missing Userid
F000000008	Invalid or Missing Password
F000000012	Password has Expired
F000000016	New Password is Invalid
F000000020	User not defined to Group
F000000024	RACINIT Failed
F000000028	Access has been Revoked
F000000032	RACF not Active
F000000036	Group Access Revoked
F000000100	Userid in Use
F000000108	Server Terminated by Cancel
F000000112	Server terminated by Closedown

Copyright 1992, Apple Computer, Inc.

Keywords: <None>

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 11040