



Tech Info Library

HyperCard 2.0: Phone Dialer Patches (7/92)

Article Created: 15 April 1991

Article Reviewed/Updated: 6 April 1994

TOPIC -----

HyperCard 2.0 includes the local area code when dialing a number from the Address book. The correction for this lies in modifying the dial handler of the stack script of the Phone Dialer stack.

DISCUSSION -----

The suggested fix is that the user first enter the local area code in the field labeled "Access Number" on the dial options card in the phone dialer. Then make the following change to the dial handler in the stack script of the Phone Dialer. This change parses out the area code, if it is local.

```
on dial theNumber
    .
    .
    .
    if international <> empty then
        -- XFCN that displays a modal dialog
        get
        PrefixDialog(dialogData(),longDistance,international,outsideLine,theNumber)
        if it = "Cancel" then exit dial
        put it into theNumber -- the user modified number
    else
        if char 1 to 3 of theNumber =areaCode
            then delete char 1 to 3 of theNumber
        else put longDistance before theNumber
        -- add the outside line character(s)
    .
    .
    .
end dial
```

The About section of the dial options on the Phone Dialer with 2.0 misleadingly states that there is a place on the card for the local area number. There actually is such a place, but it is misleading because the field is apparently labeled "Access Number", even though it is really named "Local Area Code".

However, putting the local area code in that field still won't solve the problem of HyperCard including the area code when dialing from the Address book. Some change like the one above must be made.

This article is adapted from the Claris Tech Info database.
Copyright 1994, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 14522