



Tech Info Library

AppleTalk Remote Access: PowerBook/Modem Configurations (6/96)

Article Created: 24 May 1996

Article Reviewed/Updated: 7 June 1996

TOPIC -----

How do I configure AppleTalk Remote Access (ARA) for various PowerBook computers, different versions of system software and different modems?

DISCUSSION -----

The following chart provides the set up data for ARA with different PowerBook and modem configurations listed in the following format:

Begin_Table

Computer model and modem type tested:	Others PowerBook models that should be compatible with this modem
---------------------------------------	---

Compatible system software version	
PowerBook(PB) [setup] version: configuration	
Express Modem (EM) version: configuration	
CCL: Modem script selection	
Port name in Remote Access Setup	

PowerBook 170 with ExpressModem 2400: 100, 140

Sys 7.1	Sys 7.1
PowerBook v 7.1: Internal Modem	PowerBook v 7.1.2: Internal Modem
CCL: Apple Modem 2400	CCL: Apple Modem 2400
Modem Port	Modem Port

Sys 7.1	Sys 7.1
PowerBook v 7.1.3: Internal Modem	PowerBook v 7.3: Internal Modem
CCL: Apple Modem 2400	CCL: Apple Modem 2400
Modem Port	Modem Port

Sys 7.1	
PowerBook v 7.1.2: Internal Modem	
CCL: Apple Modem 2400	
Modem Port	

Sys 7.5	Sys 7.5
---------	---------

PB Setup v 7.3.1: Internal Modem
CCL: Apple Modem 2400
Modem Port

PB Setup v 7.3.1: Internal Modem
CCL: Apple Modem 2400
Modem Port

Sys 7.5
PB Setup v 7.3.1: Internal Modem
CCL: Apple Modem 2400
Modem Port

Sys 7.5
PB Setup v 7.3.1: Internal Modem
CCL: Apple Modem 2400
Modem Port

NOTE: These computers do not require the Express Modem control panel be installed.

PowerBook 180c with Express Modem 14400: 160, 165, 165c, 180

Sys 7.1
PowerBook v 7.1: External Modem
EM v 1.2.2
CCL: EM 14400
Modem Port -- Doesn't work

Sys 7.1
PowerBook v 7.1.2: External Modem
EM v 1.0.4
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PowerBook v 7.1.3: External Modem
EM v 1.1.2
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PowerBook v 7.3: NA
EM v 1.5.3
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PB Setup v 7.1.2: External Modem
EM v 2.0
CCL: EM 14400
Internal Modem -- Doesn't work

Sys 7.5
PB Setup v 7.3.1: NA
EM v 1.0.4
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: Normal
EM v 1.1.2
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: NA
EM v 1.5.3
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: NA
EM v 2.0
CCL: EM ARA 2.x
Internal Modem

Power Macintosh: Desktop models

Sys 7.1.2
EM v1.5.1
CCL: GeoPort Telecom
GeoPort

Sys 7.1.2
EM v2.0
CCL: GeoPort Telecom ARA 2.x
Modem or Printer port (the serial port
where modem is connected)

Sys 7.5
EM v1.5.1
CCL: GeoPort Telecom
GeoPort

Sys 7.5
EM v2.0
CCL: GeoPort Telecom ARA 2.x
Modem or Printer port (the serial port
where modem is connected)

PowerBook 520c: 520, 540, 540c

Sys 7.1
PBSetup v 7.3.1: Normal
PowerPort 500 v2.0.8

CCL: GV Mercury/Gold/Silver 1.0

Internal Modem

Sys 7.1
PBSetup v 7.3.1: NA
PowerPort for 500 & Duo series v 2.5:
Normal
CCL: GV Mercury/Gold/Silver 1.0 or GV
High Speed for ARA 2.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: Normal
PowerPort 500 v2.0.8:

CCL: GV Mercury/Gold/Silver 1.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: NA
PowerPort for 500 & Duo series v 2.5:
Normal
CCL: GV High Speed for ARA 2.0
Internal Modem

PowerBook 250: 210, 230, 270, 280

Sys 7.1
PowerBook v 7.1: External Modem
EM v 1.2.2
CCL: EM 14400
Modem Port -- Doesn't work

Sys 7.1
PowerBook v 7.1.2: External Modem
EM v 1.0.4
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PowerBook v 7.1.3: External Modem
EM v 1.1.2
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PowerBook v 7.3.1: NA
EM v 1.5.3
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.1
PowerBook v 7.3.1: NA
EM v 2.0
CCL: EM ARA 2.x
Internal Modem

Sys 7.5
PB Setup v 7.3.1: Normal
EM v 1.0.4
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.5
PB Setup v 7.3.1: Normal
EM v 1.1.2
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

Sys 7.5

Sys 7.5

PB Setup v 7.3.1: NA
EM v 1.5.3
CCL: EM 14400 or EM for ARA 2.0
Internal Modem

PB Setup v 7.3.1: NA
EM v 2.0
CCL: EM for ARA 2.0
Internal Modem

End_Table

Article Change History:
07 Jun 1996 - Corrected spelling error.

Copyright 1996, Apple Computer, Inc.

Keywords: kpbook,ksts,ktable

=====

This information is from the Apple Technical Information Library.

19960610 07:11:28.00

Tech Info Library Article Number: 19862