



Tech Info Library

System Errors 7.0.1: Uncommon Codes

Article Created: 31 January 1992

Article Change History

09/25/92 - REVIEWED

- For technical accuracy.

TOPIC -----

These lists are maintained with MPW SysErr.a and in Inside Macintosh Volume VI (c) Addison-Wesley 1991. The last change was for system software version 7.0.1, on Thursday, June 20, 1991.

Here's an explanation of two symbols used in the lists:

[Items listed in brackets are old result code meanings]

???? This information wasn't available.

DISCUSSION -----

Internal File System Errors

1	chNoBuf	no free cache buffers (all in use)
2	chInUse	requested block in use
3	chnotfound	requested block not found
4	chNotInUse	block being released was not in use
16	fxRangeErr	file position beyond mapped range
17	fxOvFlErr	extents file overflow
32	btnotfound	record not found
33	btexists	record already exists
34	btnospace	no available space
35	btnoFit	record doesn't fit in node
36	btbadNode	bad node detected
37	btbadHdr	bad BTree header record detected
48	cmnotfound	CNode not found
49	cmexists	CNode already exists
50	cmnotempty	directory CNode not empty (valence = 0)
51	cmRootCN	invalid reference to root CNode
52	cmbadnews	detected bad catalog structure
53	cmFThdDirErr	thread belongs to a directory not a file

54 cmFThdGone file thread doesn't exist
64 dsBadRotate bad BTree rotate

Slot Declaration ROM Manager Errors

1 siInitSDTblErr slot int dispatch table could not be initialized.
2 siInitVBLQsErr VBLqueues for all slots could not be initialized.
3 siInitSPTblErr slot priority table could not be initialized.
10 sdmJTInitErr SDM Jump Table could not be initialized.
11 sdmInitErr SDM could not be initialized.
12 sdmSRTInitErr Slot Resource Table could not be initialized.
13 sdmPRAMInitErr Slot PRAM could not be initialized.
14 sdmPriInitErr Cards could not be initialized.

HD20 Driver Errors

16 wrtHsLw HSHK low before starting
17 wrtHSLwTO Time out waiting for HSHK to go low
19 wrtHSHighTO Time out waiting for HSHK to go high
32 rdHsHi HSHK high before starting
33 rdSyncTO Time out waiting for sync (\$AA) bye
34 rdGroupTO Time out waiting for group
36 rdHoffSyncTO Time out waiting for sync after holdoff
37 rdHsHiTO Time out waiting for HSHK high
38 rdChksumErr Checksum error on response packet
48 invalidResp First byte in response packet was wrong
49 sqncNumErr Sequence number in response packet was wrong
50 dNumberErr Drive number in response packet was wrong
64 noResp No response packet ever received

SCSI Manager Errors

2 scCommErr Communications error (operations timeout)
3 scArbNBErr Arbitration failed during SCSIGet - Bus busy
4 scBadparmsErr Bad parameter or TIB opcode
5 scPhaseErr SCSI bus not in correct phase for operation
6 scCompareErr SCSI Manager busy with another operation when SCSIGet was called
7 scMgrBusyErr SCSI Manager busy with another operation when SCSIGet was called
8 scSequenceErr Attempted operation is out of sequence - e.g., calling SCSISelect before doing SCSIGet
9 scBusTOErr Bus timeout before data ready on SCSIIRblind and SCSIWblind
10 scComplPhaseErr SCSIComplete failed - bus not in Status phase

Serial Driver Error Masks

1 swOverrunErr Serial Driver overrun error
16 parityErr Serial parity error
32 hwOverrunErr Serial hardware overrun
64 framingErr Serial framing error

Miscellaneous Result Code

1 evtNotEnb Event not enabled at PostEvent

CDev Errors

0	cdevMemErr	Memory shortfall; alert user please
1	cdevResErr	Couldn't get a needed resource; alert
3	cdevUnset	cdevValue is initialized to this
-1	cdevGenErr	General error; gray cdev w/o alert

Script Manager Errors

0	smNotTruncated	No truncation was necessary
1	smTruncated	Truncation performed
-1	smTruncErr	General error

Communications Toolbox Errors

0	ctbuNoErr	????
-1	ctbuGenericError	????

Communications Resource Manager Errors

0	crmNoErr	????
-1	crmGenericError	????

Connection Manager Errors

0	cmNoErr	????
1	cmRejected	????
2	cmFailed	????
3	cmTimeOut	????
4	cmNotOpen	????
5	cmNotClosed	????
6	cmNoRequestPending	????
7	cmNotSupported	????
8	cmNoTools	????
9	cmUserCancel	????
11	cmUnknownError	????
-1	cmGenericError	????

File Transfer Manager Errors

0	ftNoErr	????
1	ftRejected	????
2	ftFailed	????
3	ftTimeOut	????
4	ftTooManyRetry	????
5	ftNotEnoughDSpace	????
6	ftRemoteCancel	????
7	ftWrongFormat	????
8	ftNoTools	????
9	ftUserCancel	????
10	ftNotSupported	????
11	ftUnknownError	????
-1	ftGenericError	????

Midi Manager MIDIPacket Errors

1	midiOverflowErr	????
2	midiSCCErr	????
3	midiPacketErr	????
255	midiMaxErr	all command words less than this are errors

Terminal Manager Errors

0	tmNoErr	????
1	tmNotSent	????
2	tmEnvironChanged	????
7	tmNotSupported	????
8	tmNoTools	????
11	tmUnknownError	????
-1	tmGenericError	????

AppleTalk Errors

-1	overrunErr	???? (returned by ReadPacket & ReadRest routines)
-2	crcErr	????
-3	underrunErr	????
-4	lengthErr	????

System Errors to put up msg dialogs

-10	dsMacsBugInstalled	say "MacsBug Installed"
-11	dsDisassemblerInstalled	say "Disassembler Installed"
-12	dsHD20Installed	say "HD20 Startup"

Copyright 1992, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 9808