



Tech Info Library

System 7: Diagnosing System Bombs

Article Created: 28 February 1991

Article Last Reviewed: 22 July 1992

Article Last Updated: 22 July 1992

TOPIC -----

I've installed System 7 and it bombs. What should I do?

DISCUSSION -----

If your system bombs, proceed as follows:

- 1) Restart your Macintosh while holding down the Shift key, and release it when the desktop appears. This action causes most of your system extensions (INITs) and control panels not to load when the system boots. (Note: In System 7, INITs are referred to as "system extensions.") After you have removed your INITs and control panels, take each one, one-by-one, and drag it to the System Folder and restart. If the system bombs again, you will be able to tell which INIT, control panel, or combination of them is causing the crash.
- 2) Open your System folder and remove all of your extensions and control panels by placing them in a separate folder outside the System Folder. Examine the system extensions and verify that you are using the current version. If necessary, contact the product developer to determine which is the current version.

If your Macintosh computer still does not start up, continue to step 3.

- 3) Restart from one of the System 7 floppies. In the System 7 disk suite, the bootable floppy is the "Disk Tools" disk (both 800K and 1.4M).
- 4) Move any fonts, desk accessories, extensions, control panels, and preference files that you want to keep from the System Folder to another folder on your hard disk. Drag the remainder of the System Folder to the trash and empty the trash.
- 5) Do a "clean" install of the software by following the installation guidelines in your "Macintosh User's Guide."

If your Macintosh computer still does not start up, contact your dealer.

Copyright 1991, 1992, Apple Computer, Inc.

Keywords: Sys7

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 6805