



# Tech Info Library

## Network Assistant: Sys Information Report Maximum Width (7/96)

Article Created: 28 June 1996

Article Reviewed/Updated: 11 July 1996

TOPIC -----

I am using Network Assistant to create a System Information report for the Macintosh computers on my network. I have a maximum of 630 pixels that can be used for the report. How can I efficiently predetermine the items I want to select for a report and stay within the 630 pixel maximum?

DISCUSSION -----

The maximum width of the System Information report is determined by the resolution of your monitor. When the screen resolution is 640 X 480 the maximum width of the report is 630 pixels. If the screen resolution is set to 1024 X 768 the maximum width of the report is 1,014 pixels.

The workstation is always the first field in the report. When you generate a new report, this field along with the report window require 167 pixels. When the monitor resolution is set to 640 x 480, you have 463 Pixels for the remaining fields.

Since you are not going to be able to get all the fields into one report, a good strategy would be to generate reports with like fields. Multiple reports can be left open for on screen viewing.

You can also print or export the report to a text file. If you want to know more about printing or exporting a report please refer to Part 3 in the Apple Network Administrator Toolkit manual page 55 "Printing and Exporting to a text file".

The table below shows the number of pixels each field uses:

Begin\_Table

System SW Version	75	Mouse Connected	75
Built-In Memory	65	Keyboard Connected	75
Virtual Memory	65	Printer Type	130
System SW Memory	75	Printer Version	65
RAM Disk Size	75	Printer Name	130
Free Disk Space	75	Network Type	75
Total Disk Space	75	Appletalk Version	75
File Sharing	60	Appletalk Zone	130

Processor	85	Appletalk Network #	75
Monitor Size	85	Appletalk Node #	75
Monitor Setting	110	TCP/IP Address	110
2nd Monitor Size	85		
2nd Monitor Setting	110		

End\_Table

This article was published in the Information Alley on 08 July 1996.

Article Change History:

11 Jul 1996 - Added keyword  
08 Jul 1996 - Added alley info.

Copyright 1996, Apple Computer, Inc.

Keywords: kalley, kanat

=====

This information is from the Apple Technical Information Library.

19960715 07:36:30.00

Tech Info Library Article Number: 20118