



Tech Info Library

Macintosh LC 520: Power On and Shut Down Problem (7/93)

Article Created: 1 July 1993

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

This article describes a power-on symptom of the Macintosh LC 520 where as soon as the power switch on the back is turned on the system boots and when Shut Down is selected, the system restarts.

DISCUSSION -----

Some of the first batch of Macintosh LC 520 Analog boards have a jumper installed at location BD11 which causes the board to power up just like an SE or a Classic (Black and White).

All one needs to do is to remove the jumper on BD 11. In some cases, there will only be a small piece of metal connecting the two pins on the connector, no plastic body. Needlenose pliers may make it easier to get a grip on the jumper. Service and manufacturing have been made aware of this situation and are screening for it.

Copyright 1993, Apple Computer, Inc.

Keywords: hts

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 12499