



Tech Info Library

Macintosh Performa 5200: How to Perform Video Adjustments (2/96)

Article Created: 24 August 1995

Article Reviewed/Updated: 26 February 1996

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

I cannot determine how to use the diagnostic cable to make a video adjustment on a Macintosh Performa 5200 computer with an internal modem. The information on the Service Source CD seems incomplete. How can I do this?

DISCUSSION -----

The diagnostic cable (Apple service part # 922-1513 Cable, Diagnostic) is used for making video adjustments on Macintosh Performa 5200 computers. This cable is used to make video adjustments such as: focus, pin cushion, and so on.

When the Macintosh Performa 5200 computer has an internal modem installed, performing these video adjustments can be a little more complicated than indicated on the Service Source CD. Before the adjustments can be made the modem must first be removed. If it is a factory installed modem from Apple, it will also have a plastic cover over the modem port preventing the use of that port, so that must be removed.

Note: The diagnostic cable only works in the modem port. It will not work in the printer or ADB port.

Preparation:

Step 1

Make AppleTalk inactive in the Chooser. Shutdown the computer.

Step 2

If the modem port is covered, because there is a factory installed internal modem, remove the plastic cover.

Step 3

If a modem is present, remove it.

To make a video adjustment on a Macintosh Performa 5200 computer, follow these steps:

Step 1

Connect the video diagnostic cable to the modem port.

Step 2

Start up from the Macintosh Test Pro CD-ROM disc.

- or -

Start up with Extensions off by holding down the Shift key during startup.

Step 3

Perform the necessary video adjustments.

Step 4

Shut down the computer.

Step 5

Remove the diagnostic cable, then replace the modem and plastic cover.

Article Change History:

26 Feb 1996 - Removed incorrect wording.

22 Sep 1995 - Added additional preparation step.

Support Information Services

Copyright 1995-96, Apple Computer, Inc.

Keywords: supt,hts

=====

This information is from the Apple Technical Information Library.

19960226 16:03:23.00

Tech Info Library Article Number: 18475