

## AudioVision 14 Display: Connecting the Monitor (7/93)

Article Created: 29 July 1993 TOPIC -----This article discusses how to connect the AudioVision 14 Display to a Macintosh that: 1) Has a built-in high density connector on the computer. 2) Doesn't have the built-in high density connetor. DISCUSSION -----Connecting the monitor to a computer that has a built-in high density connector: 1) Before you connect any cables, make sure that your computer is turned off. 2) Connect the connector end of the power cord to the monitor and the other end to the back of the computer. 3) If the back of your computer has the high-density connector simply connect the AudioVision cable to the high-density connector on the

4) You are now ready to use the monitor. You do not need to install software if your computer has a built-in high density connector. The software is already installed on the hard drive.

back of the computer.

Connecting the monitor to a computer without a built-in high density connector:

- 1) Before you connect any cables, make sure that your computer is turned off.
- 2) Connect the connector end of the power cord to the monitor and the other end to the back of the computer.
- 3) If the back of your computer DOES NOT have the high-density connector, you need to use an adapter cable, a NUBUS video card and will have to install the AudioVision software. (The adapter cable kit part number is M1243LL/A.)

- 4) Connect the adapter cable plugs (monitor, sound in, sound out, and ADB) to the back of the computer.
- 5) Connect the AudioVision high-density cable to the high-density connector on the adapter cable by firmly pushing the cable into the connector until you hear a click.
- 6) Install the AudioVision Software that provides integrated sound and video capabilities by inserting the AudioVision Installer disk into the internal floppy disk drive.
- 7) Click the Installer icon and install the software on the appropriate hard disk.

8) Once installation is complete, restart you Macintosh. Copyright 1993, Apple Computer, Inc

Keywords: <None>

\_\_\_\_\_

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 12711