



# Tech Info Library

## Anderson Jacobson AJ 1259 modem: Using it with Apple Computers

### Modem type:

Vadic 3400 and AT&T 103/212A series; 1200 (2 modes), 0-300 bps.

### Instruction set used:

None.

### Hardware configuration:

Eight LED indicators and two switches on front panel give modem/data status and control modem functions. Telephone set is needed to originate calls using telephone for dialing. Once number has been dialed, modem is selectable to either high speed (Vadic 3400 or AT&T 212) or low speed modes.

### Software configuration:

No command structure..

### Interface type:

RS-232 DB-25S (DCE) connector, full or half duplex operation.

### Modem interface packages, by computer:

#### Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

#### Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

#### Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

#### Macintosh:

MacTerm or other terminal software; Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

#### Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

NOTE: External telephone is needed for dialing called numbers.  
Apple Technical Communications

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1313