



Tech Info Library

Cermetek 1200 Modem: Using it with all Apples

Modem type:

AT&T 103 / 212A series; 1200, 0-300 bps.

Instruction set used:

Fully HAYES compatible.

Hardware configuration:

Seven LED indicators on front panel give modem and data status. Front panel switches allow voice or data operation. Call progress circuits detect dial, busy, ring-back, modem answer, or human voice. Modem runs off 117VAC, 60Hz.

Software configuration:

Microprocessor controlled intelligent modem with auto-dial and auto-answer functions.

Interface type:

RS-232 DB-25S (DCE) connector, full duplex operation.

Modem interface packages, by computer:

Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

Macintosh:

MacTerm or other terminal software; Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

Apple Technical Communications

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1324