



Tech Info Library

Apple IIc: Connecting it to a Smith-Corona TP1 printer

On the Smith-Corona TP1 interface circuit board, set the jumpers to match these specifications:

1. 9600 Baud
2. 8 Data Bits
3. No Parity
4. 1 Stop Bit

On the Apple IIc, set the "PIN" configuration using the Apple IIc utilities program. The "PIN" configuration should be set to the same specifications that are listed above.

Cable Pinout

Apple IIc	TP1
2 -----	3
3 -----	7
5 -----	20
4 -----	2

Apple Technical Communications

Keywords: <None>

=====
This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 158