



# Tech Info Library

## Super Serial Card: Cable for ImageWriter II and APM (12/96)

Article Created: 18 February 1986

Article Reviewed/Updated: 16 December 1996

TOPIC -----

Listed below are the pinouts for connecting the Super Serial Card to an ImageWriter II printer or Apple Personal Modem.

DISCUSSION -----

ImageWriter II

or

Apple Personal Modem

Super Serial Card

Circular 8	DB 25
1 <---->	6,8
2 <---->	20
3 <---->	3
4 <---->	7
5 <---->	2
6 <---->	NC
7 <---->	NC
8 <---->	7
Shield <---->	Shield

For more information, search the Tech Info Library article "ImageWriter II: Connector cables for all Apples".

Article Change History:

16 Dec 1996 - Reviewed for technical accuracy, revised formatting.

Copyright 1986-96, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19961218 09:46:46.00

Tech Info Library Article Number: 1757