



Tech Info Library

Apple IIGS: ROM Upgrade Information

This article last reviewed: 6 March 1990

TOPIC -----

I have a question about the ROM Upgrades sent to the field for the new Apple IIGS logic board.

The ROM sent to us by Support Engineering looks like two of the ROM chips on the main logic board. There were no instructions on which chip to replace. Should we have received two chips? If not, which chip is the one to be replaced?

DISCUSSION -----

The ROM that was sent goes in the socket labeled UJ9 (FFEF). The new ROM has 28 pins. If your board has a 32-pin socket at UJ9, put pin 1 of the ROM into hole 3 of the socket. With the notched end of the chip towards the front of the Apple IIGS, there should be two holes exposed on each side of the socket. If the socket has only 28 holes, pin 1 goes to hole 1.
Copyright 1990 Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 5279