Tech Info Library

# Apple IIc: Cable structure to Nec 2015 Spinwriter

```
APPLE IIC                 NEC 2015 SPINWRITER

2-------------------------3
3-------------------------7
4-------------------------2
5-------------------------19
                          4,5,6,8: Jumpered

NEC Dip switch settings:

  Switch series 1: all off except #8
  Switch series 2: all off
  Switch series 3: all off except #4,6,7,8.
Clinton Computer, MD


Keywords:  <None>

====================================================================

This information is from the Apple Technical Information Library.

19960215 11:05:19.00
```

Tech Info Library Article Number: 1447