



Tech Info Library

ImageWriter II P/C: How to Run LoopBack Self Test

This article last reviewed: 29 April 1988

DESCRIPTION: There is a way to test the interface port on the ImageWriter II without requiring a Macintosh.

1. Build a connector with pins 3 and 5 jumpered together (touching no other pins) and pins 1 and 2 jumpered.
2. Press the Print Quality switch while you Power on the IW II.
3. If a failure occurs search on HTS and GTS for the IW II communications troubleshooting procedure.

Copyright 1988 Apple Computer, Inc.

Keywords: hts

=====
This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1606