



# Tech Info Library

## Super Serial Card: Cable for DEC LA34, DEC LA120 (11/96)

Article Created: 04 December 1984

Article Reviewed/Updated: 21 November 1996

TOPIC -----

Listed below are the cable pinouts for connecting the Super Serial card to a DEC LA34 or LA120 printer.

DISCUSSION -----

### DEC LA34 Cable

-----

Super Serial Card (SSC)	Pin	Cable	Pin	Printer Connector
Frame Ground .....(FG).....	1	<----->	1.....(FG)	
Transmit Data (Tx) .....	2	<----->	3.....(Rx)	
Receive Data (Rx) .....	3			
Request to send (RTS) ....	4			
Clear To Send (CTS) ....	5			
Data Set Ready (DSR) ....	6	<----->	20....(DTR)	
Signal Ground .....(SG).....	7	<----->	7.....(SG)	
Data Carrier Detect (DCD) ....	8			
Secondary Clear To Send (SCTS) ...	19			
Data Terminal Ready (DTR) ....	20			

\* Use printer at 300 Baud.

### DEC LA120 Cable

-----

Super Serial Card (SSC)	Pin	Cable	Printer Connector
Frame Ground .....(FG).....	1	<----->	1 .....(FG)
Transmit Data (Tx) .....	2	<----->	3 .....(Rx)
Receive Data (Rx) .....	3	<----->	2 .....(Tx)
Request to send (RTS) ....	4	<----->	8 .....(DCD)
Clear To Send (CTS) ....	5	<----->	8 .....(DCD)
Data Set Ready (DSR) ....	6	<----->	20 ....(TDR)
Signal Ground .....(SG).....	7	<----->	7 .....(SG)

Data Carrier Detect (DCD) .... 8 <-----> 4 & 5 .(RTS) & (CTS)  
Secondary Clear To Send (SCTS) ... 19  
Data Terminal Ready (DTR) .... 20 <-----> 6 .....(DSR)

Article Change History:

21 Nov 1996 - Reviewed for technical accuracy, revised formatting.

Copyright 1984-96, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19961122 07:37:55.00

Tech Info Library Article Number: 932