



Tech Info Library

Super Serial Card: Cable for Qume Sprint 5 (11/96)

Article Created: 04 December 1984

Article Reviewed/Updated: 21 November 1996

TOPIC -----

Listed below are the cable pinouts for connecting the Super Serial card to a Qume Sprint 5 printer.

DISCUSSION -----

Super Serial Card (SSC)	Cable	Printer Connector
Frame Ground(FG)..... 1	<-----> 1(FG)
Transmit Data (Tx) 2	<-----> 3(Rx)
Receive Data (Rx) 3	<-----> 2(Tx)
Request to send (RTS) 4	<-----> 8(DCD)
Clear To Send (CTS) 5	<-----> 8(DCD)
Data Set Ready (DSR) 6	<-----> 20(TDR)
Signal Ground(SG)..... 7	<-----> 7(SG)
Data Carrier Detect (DCD) 8	<-----> 4 & 5	.(RTS) & (CTS)
Secondary Clear To Send (SCTS) ... 19		
Data Terminal Ready (DTR) 20	<-----> 6(DSR)

Article Change History:

21 Nov 1996 - Reviewed for technical accuracy, revised formatting.

Copyright 1984-96, Apple Computer, Inc.

Keywords: <None>

=====
This information is from the Apple Technical Information Library.

19961122 07:37:55.00

Tech Info Library Article Number: 941