

## Numeric Keypad IIe Internal Cable: Pinouts (10/94)

Article Created: 11 September 1986 Article Reviewed/Updated: 13 October 1994

TOPIC -----

What are the pinouts for the IIe numeric keypad?

DISCUSSION -----

Here is the wiring for the internal cable that goes from the Apple IIe motherboard connector to the DB-15 on the back of the Numeric Keypad IIe.

J16 14 PIN PIN DB-15 CONN. SIGNAL 1 --- 1 -- 12 -- YO 2 --- 2 -- 5 -- Y1 3 --- 3 -- 8 -- Y3 4 --- 5 -- 2 -- Y4 5 --- 6 -- 7 -- Y2 6 --- 7 -- 4 -- Y5 7 --- N/C -- N/C -- N/C 8 --- 9 -- 1 -- X7 9 --- 10 -- 6 -- X4 10 --- 11 -- 10 -- X6 9 -- X5 11 --- 12 --J16 PIN - Internal (motherboard) connector DB-15 - External connector (mounts in back of IIe with the Internal Keypad Cable (Part #590-0129)) 14-PIN - Female connector that plugs into keypad SIGNAL - What it does Article Change History: 13 Oct 1994 - Reviewed for technical accuracy, revised formatting. Support Information Services Copyright 1986-94 Apple Computer, Inc.

Keywords: <None>

\_\_\_\_\_

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1040