



Tech Info Library

Lisa/Macintosh XL: Module Compatibility?

This article last reviewed: 20 July 1988

To line up the items in the table below, print it in Monaco 9.

SYSTEM BOARDS COMPATIBILITY TABLE

```

=====
Systems:  -> |   LISA 2   |  MACINTOSH XL  |  MODIFIED
              | (Lisa 2/5 if |                 |  MACINTOSH XL
SYSTEM BOARDS: | connected to | (LISA 2/10)    |  (Screen
 (below)       | ProFile     |                 |  Modification
              |             |                 |  Kit Installed)
=====
MOTHERBOARD   |             | Same for MacXL and Modified MacXL
Board Eng #   | 620-0108-X |                 | 620-X141
-----
Apple P/N     | 661-93106  |                 | 661-93170
-----
Notes:        | 1. Has parallel | 1. No parallel connector
              | connector       | 2. Has total of 2 DB-25 connectors
              | 2. Has 3 DB-25 |
              | connectors      |
=====
I/O BOARD     |             | Same for MacXL and Modified MacXL
Board Eng #   | 620-0117-X |                 | 620-X142-X
-----
Apple P/N     | 661-93198  |                 | 661-93171
-----
Disk Contro-  |             |
ller ROM      |             |
P/N           | 341-0290   |                 | 341-0281
Rev           | B           |                 | D
Location      | 1-A        |                 | 2-A
-----
Notes:        | 1. Resistor at | 1. Resistor at R-47
              | R-47 is NOT    | IS present
              | present        |
              | 2. Has batteries | 2. No batteries
=====
CPU BOARD     | Same for Lisa 2 and Macintosh XL |
Board Eng #   |             | 620-0119-X | 620-0119-X
-----

```

Apple P/N	661-03203	661-0298 or 661-03103
-----	-----	-----
Boot ROMs		
P/Ns	341-1075 and 341-1076	341-0347 & 341-0346
Rev	H H	3A 3A
Locations	13-D 14-D	13-D 14-D
-----	-----	-----
Serialized ROM (Video State ROM)		
P/N	620-0003	341-0348

- Notes:
1. The serialized ROM must be transferred to the customer's replacement CPU board.
 2. The Macintosh XL (Lisa 2/10) CPU board can be used in the Modified Macintosh XL, provided the correct boot ROMs and serialized ROM are installed.

MEMORY BOARDS (2 identical)	Same for Lisa 2, Mac XL (Lisa 2/10), and Modified Mac XL	
Board Eng #	620-01XX-X	
-----	-----	
Apple P/N	661-93105	

VIDEO BOARD (2 identical)	Same for Lisa 2, Mac XL (Lisa 2/10), and Modified Mac XL	
Board Eng #	620-0121-X	
-----	-----	
Apple P/N	661-93107	

Interpreting the System Boards Compatibility Table

The top row (across) lists the system names for three basic configurations of Lisa 2/Macintosh XL. The first column (down) lists the names of the boards contained in the card cage and video chamber. The boxes under each system list the engineering numbers (printed near the edges of each board) and the Apple part numbers for each system board. The part numbers and rev. level for ROM on the CPU and I/O boards are included.

When inspecting or replacing system boards, use the System Boards Compatibility Table to make sure boards and ROM (part numbers and rev. level) match the information pertaining to the system you are working on.

NOTE: Any number can be in place of the "X" in the engineering numbers listed on the table.

NOTE: Refer to the Module Identification Manual for pictures of the system boards.

Copyright 1988 Apple Computer, Inc.

Keywords: HTS,CNFG

=====
This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1828