



Tech Info Library

LisaTerminal: Specifications (Discontinued)

I. LisaTerminal: A6D0300 (Discontinued)

--Includes: LisaCalc, LisaDraw, LisaGraph, LisaWrite, LisaList,
LisaProject and the Lisa Office System.

Available from Sun Remarketing,
P. O. Box 4059, Logan, Utah 84321
(801) 752-76311

1. Terminals Emulated:

- A. VT100/VT52
- B. TTY
- C. 3278 (when used with Apple Cluster Controller or AppleLine)

2. Maximum Size:

- A. Document: 1500 lines (approx. 20 pages)
- B. Copy and Paste limit: 10 pages

3. Transmission Speed (baud):

- A. Serial Ports A or B: 50, 75, 110, 134.5, 150, 200, 300, 600,
1200, 1800, 2400, 4800, 9600
- B. Serial Port B: 3600, 19200

4. Set-up Options:

- A. Parity: Even, odd or none
- B. Full- or half-duplex transmission
- C. Xon/Xoff
- D. Manual or automatic dialing (supported on Apple 300 or 1200 and
Hayes-compatible modems)
- E. Auto-repeat on/off
- F. Auto-new line on/off
- G. Wraparound on/off
- H. Answer-back message on/off
- I. Margin bell
- J. On-line/local
- K. Serial Port A or B

5. Page Layout Options:

- A. Cursor: Block or bar shape
- B. Background: White or black
- C. 80 or 132 columns
- D. Status lights on/off
- E. Characters: Upper- and lowercase
- F. Tabs and rulers

6. Terminal Control:

- A. Function keys (such as RETURN, TAB, ESC)
- B. Cursor control codes (such as NUL, ENQ, FF, DEL)
- C. Supports all VT100 and VT52 function codes
- D. Special graphic character codes

7. Special Features:

- A. Supports communication while you use other Office System documents
- B. Cut and Paste text from and to other Lisa applications
- C. Dialog boxes and forms simplify the steps in configuring the program to communicate with other terminals.
- D. Save data with the Record Lines Off Top option; scroll back through the data (not available in 3278 mode)

8. Documentation: Reference Guide

Copyright 1985, 1992, Apple Computer, Inc.

Keywords: SPECSHT

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1171