



Tech Info Library

Macintosh 21 Color Display: No Raster (3/94)

Article Created: 3 March 1994

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

The main logic board and flyback transformer assembly on a Macintosh 21-inch Color Display have been replaced, now there is no raster. High voltage is present and the CRT filaments are on. What causes this?

DISCUSSION -----

This symptom usually occurs after the flyback transformer assembly has been replaced. This module controls of the screen voltage to the CRT, if the screen control (mounted on the flyback transformer assembly) is set too low, the electron beam inside the CRT cuts off. This causes the no raster condition. Follow the video setup procedure in Service Source CD and the monitor will operate normally.

Support Information Services
Copyright 1994, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 14753