



Tech Info Library

StyleWriter printers: How to generate a test page (10/95)

Article Created: 2 October 1995

Article Reviewed/Updated: 9 October 1995

TOPIC -----

This article explains how to generate a test page with some of the StyleWriter family printers.

DISCUSSION -----

StyleWriter
=====

Step 1

Turn printer off.

Step 2

Press and hold the Form Feed button.

Step 3

Press the Power button and release both the Form Feed and Power buttons simultaneously.

Portable StyleWriter
=====

Step 1

Turn printer off.

Step 2

Press and hold FWD ADJ and REV ADJ buttons.

Step 3

Press and hold Power button. Wait for a single beep and release the power button.

Step 4

Wait for another beep and release the FWD ADJ and REV ADJ buttons.

Step 5

Immediately press the LF/FF button.

The Portable StyleWriter prints a small test pattern.

StyleWriter II
StyleWriter 1200
Color StyleWriter Pro
Color StyleWriter 2200
Color StyleWriter 2400
=====

Step 1

Turn printer off.

Step 2

Make sure the printer has paper loaded.

Step 3

Press and hold power button.

Step 4

Release power button when orange light turns off.

Support Information Services
Copyright 1995, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 18677