



# Tech Info Library

## A/UX and TCP/IP Client Delays (9/93)

Article Created: 2 September 1993

TOPIC -----

On A/UX when running any kind of TCP/IP client like ping, ftp, telnet, and so on, A/UX sits for two minutes before proceeding. Other UNIX computers can ping the A/UX computer with no delay.

DISCUSSION -----

This can happen if the loop back address is not in the /etc/hosts file. Ensure the file contains the following line (all 4 aliases are required):

```
127.0.0.1    loop lo loo localhost
```

Restart the computer and it should work as expected.

Copyright 1993, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 13187